

SignalOn® Series



5RU Chassis
(front view)

Pads / EQs / Connectors / Accessories Accessories

- Patented make-before-break attenuator pad design for uninterrupted signal balancing
- Clear attenuator pad covers and patented pad guides for simplified maintenance
- One year warranty on all passive modules
- NEBS Level 3 compliant


D3.1/CCAP™
Compliant

1.2 GHz

Specifications

Plug-in EQs: JXP-style

85 MHz MODELS				
PART NUMBER	INSERTION LOSS (dB)		LINEARITY (dB)	RETURN LOSS (dB)
	5 MHz	85 MHz	5-85 MHz	5-85 MHz
JXPEQL85-2	2.5	0.5	0.3	≥ 20
JXPEQL85-4	4.5	0.5	0.3	≥ 20
JXPEQL85-6	6.5	0.5	0.3	≥ 20
JXPEQL85-8	8.5	0.5	0.3	≥ 20




JXPEQL85-*

* = EQ Value

Specifications

Plug-in EQs: JXP-style

204 MHz MODELS				
PART NUMBER	INSERTION LOSS (dB)		LINEARITY (dB)	RETURN LOSS (dB)
	5 MHz	204 MHz	5-204 MHz	5-204 MHz
JXPEQL204-2	2.5	0.6	0.3	≥ 20
JXPEQL204-4	4.5	0.6	0.3	≥ 20
JXPEQL204-6	6.5	0.6	0.3	≥ 20
JXPEQL204-8	8.5	0.7	0.3	≥ 20




JXPEQL204-*

* = EQ Value

Specifications

Plug-in EQs: JXP-style

1.002 GHz MODELS						
PART NUMBER	VALUE (dB)	BANDWIDTH (MHz)	INSERTION LOSS (dB)		EQ TOLERANCE (dB)	RETURN LOSS (dB)
			45 MHz	1002 MHz		
N-ACC-LE-02	2	45-1002	2	1	+/- 0.5	≥ 18
N-ACC-LE-03	3	45-1002	3	1	+/- 0.5	≥ 18
N-ACC-LE-04	4	45-1002	4	1	+/- 0.5	≥ 18
N-ACC-LE-05	5	45-1002	5	1	+/- 0.5	≥ 18
N-ACC-LE-06	6	45-1002	6	1	+/- 0.5	≥ 18
N-ACC-LE-07	7	45-1002	7	1	+/- 0.5	≥ 18
N-ACC-LE-08	8	45-1002	8	1	+/- 0.5	≥ 18
N-ACC-LE-09	9	45-1002	9	1	+/- 0.5	≥ 18
N-ACC-LE-10	10	45-1002	10	1	+/- 0.5	≥ 18
N-ACC-LE-11	11	45-1002	11	1	+/- 0.5	≥ 18
N-ACC-LE-12	12	45-1002	12	1	+/- 0.5	≥ 18
N-ACC-LE-13	13	45-1002	13	1	+/- 0.5	≥ 18




* = EQ Value

Specifications

Plug-in EQs: JXP-style

1.218 GHz MODELS						
PART NUMBER	VALUE (dB)	BANDWIDTH (MHz)	INSERTION LOSS (dB)		FLATNESS (±dB)	RETURN LOSS IN/OUT (dB)
			45 MHz	1218 MHz		
JXPEQLH-02	2	45-1218	2	1	< 0.2	20
JXPEQLH-03	3	45-1218	3	1	< 0.2	20
JXPEQLH-04	4	45-1218	4	1	< 0.2	20
JXPEQLH-05	5	45-1218	5	1	< 0.2	20
JXPEQLH-06	6	45-1218	6	1	< 0.2	20
JXPEQLH-07	7	45-1218	7	1	< 0.2	20
JXPEQLH-08	8	45-1218	8	1	< 0.2	20
JXPEQLH-09	9	45-1218	9	1	< 0.2	20
JXPEQLH-10	10	45-1218	10	1	< 0.2	20
JXPEQLH-11	11	45-1218	11	1	< 0.5	18
JXPEQLH-12	12	45-1218	12	1	< 0.5	18
JXPEQLH-13	13	45-1218	13	1	< 0.5	18
JXPEQLH-14	14	45-1218	14	1	< 0.5	18
JXPEQLH-15	15	45-1218	15	1	< 0.5	18
JXPEQLH-16	16	45-1218	16	1	< 0.5	18
JXPEQLH-17	17	45-1218	17	1	< 0.5	18
JXPEQLH-18	18	45-1218	18	1	< 0.5	18
JXPEQLH-19	19	45-1218	19	1	< 0.5	18
JXPEQLH-20	20	45-1218	20	1	< 0.5	18




* = EQ Value

Specifications

Plug-in Attenuator Pads: JXP-style

1.218 GHz MODELS				
PART NUMBER	VALUE (dB)	BANDWIDTH (MHz)	INSERTION LOSS (dB Max)	RETURN LOSS (MHz)
N-ACC-AP-00	0	5-1218	< 0.15	20
N-ACC-AP-01	1	5-1218	± 0.25	20
N-ACC-AP-02	2	5-1218	± 0.25	20
N-ACC-AP-03	3	5-1218	± 0.25	20
N-ACC-AP-04	4	5-1218	± 0.25	20
N-ACC-AP-05	5	5-1218	± 0.25	20
N-ACC-AP-06	6	5-1218	± 0.25	20
N-ACC-AP-07	7	5-1218	± 0.25	20
N-ACC-AP-08	8	5-1218	± 0.25	20
N-ACC-AP-09	9	5-1218	± 0.25	20
N-ACC-AP-10	10	5-1218	± 0.25	20
N-ACC-AP-11	11	5-1218	± 0.25	20
N-ACC-AP-12	12	5-1218	± 0.25	20
N-ACC-AP-13	13	5-1218	± 0.25	20
N-ACC-AP-14	14	5-1218	± 0.25	20
N-ACC-AP-15	15	5-1218	± 0.25	20
N-ACC-AP-16	16	5-1218	± 0.5	20
N-ACC-AP-17	17	5-1218	± 0.5	20
N-ACC-AP-18	18	5-1218	± 0.5	20
N-ACC-AP-19	19	5-1218	± 0.5	20
N-ACC-AP-20	20	5-1218	± 0.5	20
N-ACC-AP-21	21	5-1218	± 0.5	20
N-ACC-AP-22	22	5-1218	± 0.5	20
N-ACC-AP-23	23	5-1218	± 0.5	20
N-ACC-AP-24	24	5-1218	± 0.5	20
N-ACC-AP-25	25	5-1218	± 0.5	20
N-ACC-AP-26	26	5-1218	± 0.5	20
N-ACC-TP-75	75 Ω Terminator	5-1218	--	20



* = Attenuator Value

NOTE:

Typical insertion loss data between upper frequency and lower frequency.

Ordering Information

Part Number	Description
Attenuator Pads (1.218 GHz)	
N-ACC-AP-XX	XX dB Pads, Qty 25 (XX = 00 through 26)
N-ACC-AP-S1	1-5 dB Pads, Five of each Pad Value, Total Qty 25
N-ACC-AP-S2	6-10 dB Pads, Five of each Pad Value, Total Qty 25
N-ACC-AP-S3	11-15 dB Pads, Five of each Pad Value, Total Qty 25
N-ACC-AP-S4	16-20 dB Pads, Five of each Pad Value, Total Qty 25
N-ACC-AP-S5	21-25 dB Pads, Five of each Pad Value, Total Qty 25
N-ACC-AP-M0	3, 6, 9, 12, 15 dB Pads, Five of each Pad Value, Total Qty 25
N-ACC-TP-75	75 ohm Termination Pads, Qty 25
Equalizer Pads	
N-ACC-LE-XX	Linear Plug-in EQ, 1 GHz (XX = 02 through 13 dB)
JXPEQL85-X	Linear Return Path JXP Plug-in EQ, 85 MHz (X = 2, 4, 6 or 8 dB)
JXPEQL204-X	Linear Return Path JXP Plug-in EQ, 204 MHz (X = 2, 4, 6 or 8 dB)
JXPEQLH-X	Linear JXP Plug-in EQ, 1.218 GHz (X = 02 through 20 dB)
DC Power Upgrade Kits	
N-ACC-PWRKIT-08B	2RU Chassis, Black – used to power 8-position
N-ACC-PWRKIT-20B	5RU Chassis, Black – used to power 20-position
Power Supply Accessories	
N-ACC-CBL-DC-DC	Power Cord for Power Supply
N-ACC-FAN	Fan Replacement Kit for Power Supply
N-ACC-FAN-01	Fan with Filter Replacement Kit for Power Supply
Patch Panels	
N-ACC-PP-08	8-port Patch Panel, F81 Connectors for use in SignalOn Chassis Dimensions: 8.64"H x 0.83"W x 1.1"D (21.95H x 2.1W x 2.79D cm) Weight: 0.24 lbs (0.11 kg)
N-ACC-PP-16	16-port Patch Panel, F81 Connectors for use in SignalOn Chassis Dimensions: 8.64"H x 1.69"W x 1.1"D (21.95H x 4.28W x 2.79D cm) Weight: 0.47 lbs (0.22 kg)
Blank Module Covers	
N-ACC-BLANK-01	Single Blank Panel Cover



SignalOn® Series is a registered trademark of ATX in the United States and/or other countries. Products or features contained herein may be covered by one or more U.S. or foreign patents. Other non-ATX product and company names mentioned in this data sheet are the property of their respective companies.

© 2019 by ATX Networks Corp. and its affiliates (collectively "ATX Networks Corp."). All rights reserved. This material may not be published, broadcast, rewritten, or redistributed. Information in this document is subject to change without notice. Rev. 10/19 (ANW1105)



ATX Networks

Tel: 289.204.7800 | Toll-Free: 866.YOUR.ATX | support@atx.com