


DIGICOMM INTERNATIONAL® 204 MHz REVERSE EQUALIZERS



Digicomm offers a complete line of 204 MHz Reverse Equalizers from 1 dB through 20 dB in 1 dB increments. The reverse equalizers are designed to produce a tilted frequency response opposite of what is produced by the coaxial cable.

Digicomm Part Number	EQ (dB) Value	FREQUENCY (MHz) VERSUS INSERTION LOSS (dB)						
		5 MHz	40 MHz	42 MHz	65 MHz	85 MHz	104 MHz	204 MHz
GM-EQREV-204M-1	1	1.2	0.9	0.9	0.8	0.7	0.6	0.4
GM-EQREV-204M-2	2	2.4	1.8	1.8	1.6	1.4	1.2	0.6
GM-EQREV-204M-3	3	3.2	2.5	2.5	2.1	1.9	1.7	0.5
GM-EQREV-204M-4	4	4.0	2.9	2.9	2.4	2.1	1.9	0.5
GM-EQREV-204M-5	5	4.9	3.5	3.4	2.8	2.3	2.0	0.5
GM-EQREV-204M-6	6	5.9	4.1	4.1	3.4	2.8	2.4	0.6
GM-EQREV-204M-7	7	6.4	4.4	4.3	3.5	2.9	2.4	0.3
GM-EQREV-204M-8	8	7.5	5.3	5.2	4.3	3.6	3.1	0.6
GM-EQREV-204M-9	9	8.3	5.9	5.8	4.8	4.0	3.4	0.7
GM-EQREV-204M-10	10	9.2	6.5	6.3	5.2	4.3	3.6	0.7
GM-EQREV-204M-11	11	10.0	6.9	6.7	5.5	4.5	3.7	0.5
GM-EQREV-204M-12	12	11.0	7.7	7.6	6.2	5.2	4.4	0.7
GM-EQREV-204M-13	13	12.1	8.3	8.1	6.8	5.7	4.8	0.9
GM-EQREV-204M-14	14	12.9	9.0	8.9	7.5	6.3	5.3	0.9
GM-EQREV-204M-15	15	13.8	9.6	9.4	7.8	6.6	5.5	0.9
GM-EQREV-204M-16	16	14.6	10.1	9.9	8.3	6.9	5.8	1.0
GM-EQREV-204M-17	17	15.4	10.6	10.4	8.6	7.2	6.0	1.1
GM-EQREV-204M-18	18	16.5	11.3	11.1	9.1	7.6	6.3	0.9
GM-EQREV-204M-19	19	17.3	11.9	11.7	9.6	8.0	6.6	0.9
GM-EQREV-204M-20	20	18.2	12.5	12.3	10.1	8.4	6.9	0.9